INSTRUCTIONS FOR OPERATION OF THE NICOLET IR SPECTROMETERS

ЈМН, 6-2008



1. Double-click the EZ OMNIC FTIR icon:

EZ OMNIC FTIR.Ink . You will see the following window:

EZ DINNEC - [Window1] EVEN The Diverse Andrew Wedge Hep				· · · · · · · · · · · · · · · · · · ·		
Smart Accessory Change						
Accessory inserted Custom E.S.P.	2 Litt	Nim Sol Seach	QC QC Day			
Multiple experiments for accessory, selections:					0	
Custom E S P./Transmission						
OK Carcel						
75-						
70-						
60						
00						

- 2. Choose the correct accessory plate from the dropdown menu (for CHEM 304, it will usually be "Custom E.S.P./Transmission" or "Transmission ESP/Transmission", depending on which instrument is being used.
- 3. (This is where most CHEM 304 students will begin.) Click the "Collect Sample" button (Col Smp). This will bring up the Collect Sample dialog box.

Å EZ 06	NIC - ICH	lact Som	ele)											en e
00 No. 1	tok Colect	View Pr	cosso Are	dyze Wed	low Hob									- 6 x
	rent. Cust		VTrániem					-						🛃 Barch Status
Col Big	Col Snp	Print.	Copy	A Parm	Clear	Absolb	A Trave	Subtract	Aut Bala	Find Plus	Nim Sol	ea. Seach	QC Cap	
Addto	new winds	peer .												· (
	100 96 Enter the Microso	Sample espectrum TO 15:31	ottile: 56 2006 () OK	Can	- 									

4. Enter a spectrum title (your sample number, or your initials and date) and click "OK". The Collect Background confirmation dialog box will appear:



Make sure there is no sample in the spectrometer and click "OK"

When the background collection is finished, you will see the background spectrum of air and the Sample Collection dialog box:



5. Place the sample in the holder and click "OK". When sample collection stops, you will see the IR spectrum of your product and the "Add to new window?" dialog box will appear:



6. Click the "Yes" button, then Click "OK" when the New Window dialog box appears:



7. To generate wavenumbers for the spectrum peaks, click the "Find Peaks" button in the toolbar:



- 8. Left single click in the window to move the Peak Reject threshold to the desired position:
- 9. Click the "Replace" button at the top right of the spectrum.

Cust	om E.S.P./	Transmi	esion				-																	1	Dent	
	AND DEF		£ no	1	Abook	Sal Sal	B		2	ind Pa	Non Sel	Seath	QC QC Crep												10	
and later	ce the onge	in spect	FUM	01.000								-	~	_	_									-4	100	eprace.
		Vie			N			ſ	w	~	M				1	1	1	A		A			1			
														42.68	3.09 1746.11		1540.44		M		1		642.05			
														ų.	1800				1328 54	1154.31		05 979.60 pp.			620.17	
						-	6. OOD									1 CBDI		1372.4		118110	1061	942.26	906.45			
						102.34		2849.21								601.03					1008.2%					174 0CD
						11.66 19.15 \$004.07	2924 70									5	0.65	1402.20						20.45 703.71		
wid 60			3500	• •	•	300	0	÷		2500	Wa		200	0	• •		9 <u>7</u> 1500		-		100	20		F	5	i.

- 10. Print the spectrum using the "Print" button in the toolbar.
- 11. Close all of the spectrum windows, and do not save any of the changes. Do not exit the application.